

AC/DC power supplies

MAA Family MAA60, 60 W



Basic specifications

| | |
|---------------------------------|----------------------------|
| Power | 60 W |
| Input current | up to 12A |
| Input voltage | ~220 (100...264) VAC |
| Output voltage | =5 VDC, =24 VDC, =27VDC |
| Efficiency..... | 81-88% |
| Case operating temperature..... | -40...+85 °C; -50...+85 °C |
| Dimensions | 61x111x24 mm |
| Warranty | 2 years |

Advantages

- ◀ Design to meet MIL-STD-810G and MIL-STD-461E
- ◀ Operation temperature from -50 °C or -40 °C (depending on version)
- ◀ Conductive cooling




Description of MAA60 on the manufacturer's website:
eng.kwsystems.ru/catalog/acdc/models/3

Order registration
+7 473 200 87 80, Global Operations Team

Technical support
Mikhail Timokhin, mtimohin@kwsystems.ru

Ordering information



Input specifications*

| Parameter | Value | |
|--------------------------------|-------|-------------------------|
| Input voltage range, VAC** | C | ~100...264 (=141...372) |
| | S | ~187...242 (=263...340) |
| Transient deviation range, VAC | C | ~100...264 |
| | S | ~176...264 |
| Transient time | S | 1 s. |
| | C | - |
| Mains frequency range, Hz | C, S | 47...440 |

Output specifications*

| Parameter | Value | | | | | |
|---------------------------------|-----------------------|------|----|----|-----|------|
| Nominal output voltage, VDC | 5 | 9 | 12 | 15 | 24 | 28 |
| Efficiency, % | 81 | 83 | 84 | 85 | 87 | 88 |
| Rated output current, A | 12 | 6.67 | 5 | 4 | 2.5 | 2.14 |
| Ripple and noise (peak-to-peak) | <2% | | | | | |
| Line and load regulation | max 2% | | | | | |
| Start-up time, ms | <500 | | | | | |
| Maximum load capacity | 45500 µF (Uout=5 VDC) | | | | | |

* All specifications are valid for normal climatic conditions (ambient temp. +15...+35°C; relative humidity 45...80%; air pressure 8.6*104...10.6*104 Pa), Uin. nom., Iout. nom., unless otherwise noted.

** Maximum output power for input voltage range C (wide range) at Uout 100...187 VDC is reducing according to power derating VS input voltage diagram.

Protections

| Type of protection | |
|-------------------------------|-------------------------------------|
| Short-circuit protection* | auto recovery |
| Overload protection | Pmax<1.2 Pnom |
| Overtoltage protection level* | <125% Uout nom. |
| Overheat protection | triggers at case temperature > 85°C |

Basic specifications**


| Parameter | Value | |
|-----------------------------------|--|-------------|
| Type of connection | screw terminals and blade contacts | |
| Protection level | IP20 | |
| Case temperature, operating | «N» | -40...+85°C |
| | «P» | -50...+85°C |
| Case temperature, storage | -50...+70°C | |
| Humidity | 98% / 35°C | |
| Isolation voltage | in /case | ~1500 VAC |
| | in /out | ~1500 VAC |
| | out /case, out/out | ~500 VAC |
| Isolation resistance @ 500 VDC | ≥ 20 MΩ min | |
| Cooling | conductive, forced air | |
| Environmental influence standards | design to meet MIL-STD-810G | |
| EMC standards | EN55022 (CISPR22); design to meet MIL-STD-461E | |
| Thermal resistance case-ambient | 6.4°C / W | |
| Typical MTBF | 3 000 000Hrs | |
| Case material | metal | |
| Dimensions, mm | 111×61×23.5 | |
| Weight, kg | < 0.27 | |
| Warranty | 2 year | |

* Parameters are stated for the information purposes and could not be used at long term work, exceeding maximum output current, operating outside of a working temperatures range or when output voltage is over the range of adjustment.


** All specifications are valid for normal climatic conditions, Uin. nom., Iout. nom., unless otherwise noted.

Derating

vs Temperature




vs Input Voltage



Decreasing parts of the dashed and dash-dotted curves correspond to the maximum case temperature (+85°C for models with index «N» and «P»). Output power must not exceed the values limited by curve for a given ambient temperature.


Dimensions

Single-channel design with blade contacts



| PIN # | 1 | 2 | 3 | 4 | 5 | 6 | 7 |
|----------------|---|---|---|--------|--------|--------|--------|
| SINGLE-CHANNEL | (| L | N | +OUT 1 | +OUT 1 | -OUT 1 | -OUT 1 |

Single-channel design with terminal blocks



| PIN # | X1.1 | X1.2 | X1.3 | X2.1 | X2.2 | X2.3 | X2.4 |
|----------------|------|------|------|--------|--------|--------|--------|
| SINGLE-CHANNEL | (| L | N | +OUT 1 | +OUT 1 | -OUT 1 | -OUT 1 |



www.kwsystems.ru info@kwsystems.ru

KW Systems, LLC is the leading Russian developer and manufacturer of AC/DC converters and power supply systems for mission critical applications.

Druzinnikov str. 5B, Voronezh, 394026, Russia. +7 473 200-87-80

This datasheet is valid for the following units: MAA60-1C05CXX, MAA60-1C09CXX, MAA60-1C12CXX, MAA60-1C15CXX, MAA60-1C24CXX, MAA60-1C28CXX, MAA60-1S05CXX, MAA60-1S09CXX, MAA60-1S12CXX, MAA60-1S15CXX, MAA60-1S24CXX, MAA60-1S28CXX.